



KINO FLO
Lighting Systems

DIVA LITE[®] LED



Diva-Lite® 21/31/41



Diva-Lite® LED has five menu options. In the white menu, the Kelvin range is from 2700K to 6500K with **Dimming, Kelvin** and **Green/Magenta** control channels. In the color menu, Kelvin range is from 2500K to 9900K, with three additional channels, **Gel, Hue Angle** and **Saturation**. The Gel channel includes Kino Flo presets and over 100 well-known lighting gels. The second color menu provides individual **RGB** (red, green, blue) control. The **CIExy** menu allows you to enter xy coordinates. The **FX** (Effects) menu has custom presets like Candle, Fire, TV, Police, Lightning, Paparazzi, Pulse and Scroll.

The Diva-Lite LED comes with standard DMX, wireless DMX (Lumen Radio®), universal voltage input 100-240VAC and 24VDC. SnapBag Softbox and SnapBag accessories are also available.


Features include:

- Kelvin presets & custom settings, 2500K-9900K
- Green/Magenta control
- Kino Flo presets and Gels
- Dial in any color through Hue Angle and Saturation control
- RGB control
- CIE xy
- FX (Effects) control
- Camera Profiles (LUTs)
- Color Space
- Universal input 100VAC-240VAC and 24VDC
- Manual and DMX dimming, DMX wireless (Lumen Radio)
- Honeycomb Louver, Center Mount and Yoke Mount

▼ Diva-Lite 21 LED DMX Center



DIV-L21XCU
Diva-Lite 21 LED DMX
Center Mount, Univ



LVR-SL290-P
Diva-Lite 21
Louver/HP, 90°
(Included)




MTP-LBC
Kino 41 Lollipop w/
Baby Receiver Curve
(16mm) (Included)

▼ Diva-Lite 21 LED DMX Yoke



DIV-L21XYU
Diva-Lite 21 LED DMX
Yoke Mount, Univ




LVR-SL290-P
Diva-Lite 21
Louver/HP, 90°
(Included)

▼ Diva-Lite 31 LED DMX Center



DIV-L31XCU
Diva-Lite 31 LED DMX
Center Mount, Univ



LVR-SL390-P
Diva-Lite 31
Louver/HP, 90°
(Included)




MTP-LBC
Kino 41 Lollipop w/
Baby Receiver Curve
(16mm) (Included)

▼ Diva-Lite 31 LED DMX Yoke



DIV-L31XYU
Diva-Lite 31 LED DMX
Yoke Mount, Univ



LVR-SL390-P
Diva-Lite 31
Louver/HP, 90°
(Included)

Diva-Lite® 21/31/41

▼ Photometrics

Diva-Lite 21

FC	508	154	70	40	26	18	14	11	9	7
Feet	2	4	6	8	10	12	14	16	18	20
LUX	7113	2409	1121	634	412	288	212	164	131	106
Meters	0.5	1	1.5	2	2.5	3	3.5	4	4.5	5

Diva-Lite 31

FC	510	161	75	43	28	20	15	11	9	8
Feet	2	4	6	8	10	12	14	16	18	20
LUX	7270	2470	1190	683	445	312	233	181	146	117
Meters	0.5	1	1.5	2	2.5	3	3.5	4	4.5	5

Diva-Lite 41

FC	481	161	77	45	29	21	16	12	10	8
Feet	2	4	6	8	10	12	14	16	18	20
LUX	6840	2450	1210	712	462	325	242	189	153	123
Meters	0.5	1	1.5	2	2.5	3	3.5	4	4.5	5


▼ Fixture Specifications

Fixture	Input Voltage VAC	Amps VAC	Input Voltage VDC	Amps 24VDC	Kelvin Range	Dimming Range	Dimensions	Weight
Diva-Lite 21 Center	100-240VAC, 50/60Hz, 150W	1.25A 0.65A	18-36VDC, 150W	6.25A	2500-9900	100%-1%	23.5 x 4.5 x 11.5" (60 x 11.5 x 29cm)	12 lb (5.5kg)
Diva-Lite 21 Yoke	100-240VAC, 50/60Hz, 150W	1.25A 0.65A	18-36VDC, 150W	6.25A	2500-9900	100%-1%	28.5 x 4.5 x 14.5" (72.5 x 11.5 x 37cm)	13 lb (6kg)
Diva-Lite 31 Center	100-240VAC, 50/60Hz, 150W	1.25A 0.65A	18-36VDC, 150W	6.25A	2500-9900	100%-1%	37.5 x 4.5 x 9.5" (95 x 11.5 x 24cm)	14 lb (6.5kg)
Diva-Lite 31 Yoke	100-240VAC, 50/60Hz, 150W	1.25A 0.65A	18-36VDC, 150W	6.25A	2500-9900	100%-1%	42 x 4.5 x 12" (107 x 11.5 x 30.5cm)	14.5 lb (6.5kg)
Diva-Lite 41 Center	100-240VAC, 50/60Hz, 150W	1.25A 0.65A	18-36VDC, 150W	6.25A	2500-9900	100%-1%	49.5 x 4.5 x 7.5" (126 x 11.5 x 19cm)	15 lb (7kg)
Diva-Lite 41 Yoke	100-240VAC, 50/60Hz, 150W	1.25A 0.65A	18-36VDC, 150W	6.25A	2500-9900	100%-1%	56 x 4.5 x 10" (142 x 11.5 x 25.5cm)	15.5 lb (7kg)

▼ Diva-Lite 41 LED DMX Center



DIV-L41XCU
Diva-Lite 41 LED DMX
Center Mount, Univ



LVR-SL490-P
Diva-Lite 41
Louver/HP, 90°
(Included)




MTP-LBC
Kino 41 Lollipop w/
Baby Receiver Curve
(16mm) (Included)

▼ Diva-Lite 41 LED DMX Yoke



DIV-L41XYU
Diva-Lite 41 LED DMX
Yoke Mount, Univ



LVR-SL490-P
Diva-Lite 41
Louver/HP, 90°
(Included)

▼ Details



Diva 41



▼ Diva-Lite LED DMX Kits



KIT-DL21XU

Diva-Lite 21 LED DMX Center Kit w/ Travel Case, Univ

Contents

- 1 Diva-Lite 21 LED DMX Center, Univ
- 1 Travel Case

Dimensions

28.5 x 8.5 x 16"
(72.5 x 22 x 41cm)

Weight

22.5 lb
(10kg)



KIT-DL31XU

Diva-Lite 31 LED DMX Center Kit w/ Travel Case, Univ

Contents

- 1 Diva-Lite 31 LED DMX Center, Univ
- 1 Travel Case

Dimensions

45.5 x 9 x 16.5"
(116 x 23 x 42cm)

Weight

33.5 lb
(15kg)

Diva-Lite® 21/31/41

▼ Diva-Lite LED DMX Accessories/Cases



SYS-BK12
Block/KF21 Single Battery System,
140Whr, 28.8V (2 x Battery)



MTP-B41F
Kino Offset
w/ Baby Receiver (16mm)



STD-M30
Medium Duty, 30"
STD-M36
Medium Duty, 36"




BRD-D21
Diva-Lite 21 Barndoors (Set of 2)
BRD-D31
Diva-Lite 31 Barndoors (Set of 2)
BRD-D41
Diva-Lite 41 Barndoors (Set of 2)



MTP-LBC
Kino 41 Lollipop
w/ Baby Receiver Curve (16mm)



STD-D1
Reverse Stand



LVR-SL260-P
Diva-Lite 21 Louver/HP, 60"
LVR-SL360-P
Diva-Lite 31 Louver/HP, 60"
LVR-SL460-P
Diva-Lite 41 Louver/HP, 60"



MTP-LBS
Kino 41 Lollipop
w/ Baby Receiver Short (16mm)



KAS-DL21-C
Diva-Lite 21 Travel Case



DFS-FS21-S
Diva-Lite 21 SnapBag w/ 2 x Diffusion
DFS-FS31-S
Diva-Lite 31 SnapBag w/ 2 x Diffusion
DFS-FS41-S
Diva-Lite 41 SnapBag w/ 2 x Diffusion



MTP-I40
Baby Receiver Assembly
for Yoke (16mm)



KAS-DL31-C
Diva-Lite 31 Travel Case



LVR-FS240-S
Diva-Lite 21 SnapGrid, 40"
LVR-FS340-S
Diva-Lite 31 SnapGrid, 40"
LVR-FS440-S
Diva-Lite 41 SnapGrid, 40"



MTP-I80
Junior Pin Assembly
for Yoke (28mm)



7010055
Diva-Lite 21 Yoke Assembly
7010057
Diva-Lite 31 Yoke Assembly
7010059
Diva-Lite 41 Yoke Assembly



Kino Flo Lighting Systems
2840 North Hollywood Way
Burbank, CA 91505
+1 818 767 6528 voice

www.kinoflo.com
©Kino Flo Diva-Lite 21/31/41
No. 3110116 Rev C